



Contents

Intellectual Property Rights Notice..... ii
Technical Support..... vi

Hardware Recommendations and Certifications.....8

- Recommended Graphics Boards..... 9
- Recommended Workstation Desktop and Laptop/Notebook Hardware..... 12
- HyperWorks 2020 Solver Hardware Configuration Recommendations..... 17
- Recommended GPU Computing Processor List for OptiStruct..... 23
- Additional Information on Driver Installations..... 24

Intellectual Property Rights Notice

Copyrights, Trademarks, Trade Secrets, Patents & Third Party Software Licenses

Altair HyperWorks 2020 Copyright 1986-2020

The Platform for Innovation™

Altair Engineering Inc. Copyright © 1986-2020. All Rights Reserved.



Note: Pre-release versions of Altair software are provided 'as is', without warranty of any kind. Usage of pre-release versions is strictly limited to non-production purposes.

Altair HyperWorks™ - The Platform for Innovation™

Altair AcuConsole™ ©2006-2020

Altair AcuSolve™ ©1997-2020

Altair ElectroFlo™ ©1992-2020

Altair ESAComp™ ©1992-2020

Altair Feko™ ©1999-2014 Altair Development S.A. (Pty) Ltd.; ©2014-2020 Altair Engineering Inc.

Altair Flux™ ©1983-2020

Altair FluxMotor™ ©2017-2020

Altair HyperCrash™ ©2001-2020

Altair HyperGraph™ ©1995-2020

Altair HyperLife™ ©1990-2020

Altair HyperMesh™ ©1990-2020

Altair HyperStudy™ ©1999-2020

Altair HyperView™ ©1999-2020

Altair Virtual Wind Tunnel™ ©2012-2020

Altair HyperXtrude™ ©1999-2020

Altair Manufacturing Solver™ ©2011-2020

Altair MotionSolve™ ©2002-2020

Altair MotionView™ ©1993-2020

Altair Multiscale Designer™ ©2011-2020

Altair OptiStruct™ ©1996-2020

Altair Radioss™ ©1986-2020

Altair Seam™ ©1985-2019 Cambridge Collaborative, Inc., © 2019-2020 Altair Engineering Inc.

Altair SimLab™ ©2004-2020

Altair SimSolid™ ©2015-2020

Altair nanoFluidX™ ©2013-2018 Fluidyna GmbH, © 2018-2020 Altair Engineering Inc.

Altair ultraFluidX™ ©2010-2018 Fluidyna GmbH, © 2018-2020 Altair Engineering Inc.

Altair WinProp™ ©2000-2020

Altair ConnectMe™ ©2014-2020

Plus other products from the Altair solidThinking Platform.

Altair Packaged Solution Offerings (PSOs)

Altair Automated Reporting Director™ ©2008-2020

Altair GeoMechanics Director™ ©2011-2020

Altair Impact Simulation Director™ ©2010-2020

Altair Model Mesher Director™ ©2010-2020

Altair NVH Director™ ©2010-2020

Altair Squeak and Rattle Director™ ©2012-2020

Altair Virtual Gauge Director™ ©2012-2020

Altair Weight Analytics™ ©2013-2020

Altair Weld Certification Director™ ©2014-2020

Altair Multi-Disciplinary Optimization Director™ ©2012-2020

Altair solidThinking - Where Innovation Takes Shape™

Altair Inspire™ ©2009-2020 including Altair Inspire Motion, Altair Inspire Structures, and Altair Inspire Print3D

Altair Inspire™ Extrude-Metal ©1996-2020 (formerly Click2Extrude®-Metal)

Altair Inspire™ Extrude-Polymer ©1996-2020 (formerly Click2Extrude®-Polymer)

Altair Inspire™ Cast ©2011-2020 (formerly Click2Cast®)

Altair Inspire™ Form ©1998-2020 (formerly Click2Form®)

Altair Inspire Render™ ©1993-2016 Solid Iris Technologies Software Development One PLLC, ©2016-2020 Altair Engineering Inc (initial release-Q3 2019, formerly Thea Studio)

Altair Inspire™ Studio ©1993-2020 (formerly 'Evolve')

Altair Compose® ©2007-2020 (formerly solidThinking Compose®)

Altair Activate® ©1989-2020 (formerly solidThinking Activate®)

Altair Embed® ©1989-2020 (formerly solidThinking Embed®)

- **Altair Embed SE** ©1989-2020 (formerly solidThinking Embed® SE)
- **Altair Embed/Digital Power Designer** ©2012-2020

Altair SimLab™ ©2004-2020

Altair One™ ©1994-2020

Altair PBSWorks™ - Accelerating Innovation in the Cloud™

Altair PBS Professional® ©1994-2020

Altair Control™ ©2008-2020; (formerly **PBS Control**)

Altair Access™ ©2008-2020; (formerly **PBS Access**)

Altair Accelerator™ ©1995-2020; (formerly **NetworkComputer**)

Altair Accelerator™ Plus ©1995-2020; (formerly **WorkloadXelerator**)

Altair FlowTracer™ ©1995-2020; (formerly **FlowTracer**)

Altair Allocator™ ©1995-2020; (formerly **LicenseAllocator**)

Altair Monitor™ ©1995-2020; (formerly **LicenseMonitor**)

Altair Hero™ ©1995-2020; (formerly **HERO**)

Altair Software Asset Optimization™ (SAO) ©2007-2020



Note:

Compute Manager™ ©2012-2017 is now part of **Altair Access**

Display Manager™ ©2013-2017 is now part of **Altair Access**

PBS Application Services™ ©2008-2017 is now part of **Altair Access**

PBS Analytics™ ©2008-2017 is now part of **Altair Control**

PBS Desktop™ ©2008-2012 is now part of **Altair Access**, specifically **Altair Access desktop**, which also has **Altair Access web** and **Altair Access mobile**

e-Compute™ ©2000-2010 was replaced by "**Compute Manager**" which is now **Altair Access**

Altair KnowledgeWorks™

Altair Knowledge Studio® ©1994-2020 Angoss Software Corporation, ©2020 Altair Engineering Inc.

Altair Knowledge Studio for Apache Spark ©1994-2020 Angoss Software Corporation, ©2020 Altair Engineering Inc.

Altair Knowledge Seeker™ ©1994-2020 Angoss Software Corporation, ©2020 Altair Engineering Inc.

Altair Knowledge Hub™ ©2017-2020 Datawatch Corporation, ©2020 Altair Engineering Inc.

Altair Monarch™ ©1996-2020 Datawatch Corporation, ©2020 Altair Engineering Inc.

Altair Monarch Server ©1996-2020 Datawatch Corporation, ©2020 Altair Engineering Inc.

Altair Panopticon™ ©2004-2020 Datawatch Corporation, © 2020 Altair Engineering Inc.

Altair SmartWorks™

Altair SmartCore™ ©2011-2020 Altair Engineering Inc.

Altair SmartEdge™ ©2011-2020 Altair Engineering Inc.

Altair SmartSight™ ©2011-2020 Altair Engineering Inc.

Altair intellectual property rights are protected under U.S. and international laws and treaties. Additionally, Altair software is protected under patent #6,859,792 and other patents pending. All other marks are the property of their respective owners.

ALTAIR ENGINEERING INC. Proprietary and Confidential. Contains Trade Secret Information.

Not for use or disclosure outside of Altair and its licensed clients. Information contained in Altair software shall not be decompiled, disassembled, "unlocked", reverse translated, reverse engineered, or publicly displayed or publicly performed in any manner. Usage of the software is only as explicitly permitted in the end user software license agreement. Copyright notice does not imply publication.

Third party software licenses

AcuConsole contains material licensed from Intelligent Light (www.ilight.com) and used by permission.

Software Security Measures:

Altair Engineering Inc. and its subsidiaries and affiliates reserve the right to embed software security mechanisms in the Software for the purpose of detecting the installation and/or use of illegal copies of the Software. The Software may collect and transmit non-proprietary data about those illegal copies. Data collected will not include any customer data created by or used in connection with the Software and will not be provided to any third party, except as may be required by law or legal process or to enforce our rights with respect to the use of any illegal copies of the Software. By using the Software, each user consents to such detection and collection of data, as well as its transmission and use if an illegal copy of the Software is detected. No steps may be taken to avoid or detect the purpose of any such security mechanisms.

Technical Support

Altair provides comprehensive software support via web FAQs, tutorials, training classes, telephone and e-mail.

Altair Support on the World Wide Web

The Altair web site is a valuable online companion to Altair software. Visit www.altairhyperworks.com for tips and tricks, training course schedules, training/tutorial videos, and other useful information.

Altair Training Classes

Altair training courses provide a hands-on introduction to our products, focusing on overall functionality. Courses are conducted at our main and regional offices or at your facility. If you are interested in training at your facility, please contact your account manager for more details. If you do not know who your account manager is, please send an e-mail to training@altair.com and your account manager will contact you.

Telephone and E-mail

When contacting Altair support, please specify the product and version number you are using along with a detailed description of the problem. Many times, it is very beneficial for the support engineer to know what type of workstation, operating system, RAM, and graphics board you have, so please have that information ready. If you send an e-mail, please specify the workstation type, operating system, RAM, and graphics board information in the e-mail.

To contact an Altair support representative, reference the following table or the information available on the HyperWorks website: www.altair.com/customer-support/.

Location	Telephone	E-mail
Australia	64.9.413.7981	anzsupport@altair.com
Brazil	55.11.3884.0414	br_support@altair.com
Canada	416.447.6463	support@altairengineering.ca
China	86.400.619.6186	support@altair.com.cn
France	33.1.4133.0992	francesupport@altair.com
Germany	49.7031.6208.22	hwsupport@altair.de
Greece	30 231 0473311	eesupport@altair.com
India	91.80.6629.4500 1.800.425.0234 (toll free)	support@india.altair.com
Israel		israelsupport@altair.com

Location	Telephone	E-mail
Italy	39.800.905.595	support@altairengineering.it
Japan	81.3.6225.5830	support@altairjp.co.jp
Malaysia		aseansupport@altair.com
Mexico	55.56.58.68.08	mx-support@altair.com
New Zealand	64.9.413.7981	anzsupport@altair.com
South Africa	27 21 8311500	support@altair.co.za
South Korea	82.70.4050.9200	support@altair.co.kr
Spain	34 910 810 080	support-spain@altair.com
Sweden	46.46.460.2828	support@altair.se
United Kingdom	01926.468.600	support@uk.altair.com
United States	248.614.2425	hwsupport@altair.com

For questions or comments about this help system, send an email to connect@altair.com.

In addition, the following countries have resellers for Altair Engineering: Colombia, Czech Republic, Ecuador, Israel, Russia, Netherlands, Turkey, Poland, Singapore, Vietnam, Indonesia

Official offices with resellers: Canada, China, France, Germany, India, Malaysia, Italy, Japan, Korea, Spain, Taiwan, United Kingdom, USA

See www.altair.com for complete contact information.

Hardware Recommendations and Certifications

View the most recent recommended graphic boards, laptops and desktop hardware configurations.


This chapter covers the following:

- [Recommended Graphics Boards](#) (p. 9)
- [Recommended Workstation Desktop and Laptop/Notebook Hardware](#) (p. 12)
- [HyperWorks 2020 Solver Hardware Configuration Recommendations](#) (p. 17)
- [Recommended GPU Computing Processor List for OptiStruct](#) (p. 23)
- [Additional Information on Driver Installations](#) (p. 24)

Recommended Graphics Boards

Recommended CAE/CAD graphic boards to use with HyperWorks applications.

The most recent vendor/manufacturer drivers should be used and all driver support for these cards should be addressed to the appropriate manufacturer of the graphic board.

 **Note:** We no longer will support AMD graphics cards on Linux x86_64 operating systems in HyperWorks 2020 and higher products.

AMD Graphics Cards

Products	GPU Model	Driver Version
Raedon™ Pro	WX 9100	<i>Windows 7/10 (64-bit)</i> 19.Q2 / 19.Q4
	W5700*	
	WX 8200	<i>*Windows 7/10 (64-bit)</i> 20.Q1
	W5500*	
	WX 7100	<i>Linux (64-bit)</i> Not Supported
	WX 5100	
	WX 4100	
	WX 3200	
	WX 3100	
WX 2100		
FirePro™ 3D	W9100	<i>Windows 7/10 (64-bit)</i> 19.Q2 / 19.Q4
	W8100	
	W7100	<i>Linux (64-bit)</i> Not Supported
	W5100	
	W4100	
	W2100	
Raedon™ Pro Mobility	WX 7130	<i>Windows 7/10 (64-bit)</i> 19.Q2 / 19.Q4
	WX 7100	
	WX 4170	<i>Linux (64-bit)</i> Not Supported
	WX 4150	
	WX 4130	
	WX 3100	

Products	GPU Model	Driver Version
	WX 2100	
FirePro™ 3D Mobility	W7170 W6150 W5170 W5130 W4190	Windows 7/10 (64-bit) 19.Q2 / 19.Q4 Linux (64-bit) Not Supported

NVIDIA Graphics Boards

Products	GPU Model					Driver Version
	K (Kepler)	M (Maxwell)	P (Pascal)	V (Volta)	RTX	
Quadro Series	K420	M2000	P400	GV100	RTX 3000	Windows 7/10 (64-bit) 431.86
	K600	M4000	P600		RTX 4000	
	K620	M5000	P620		RTX 5000	Linux (64-bit) 430.50
	K1200	M6000	P1000		RTX 6000	
	K2000		P2000		RTX 8000	
	K2200		P2200			
	K4000		P4000			
	K4200		P5000			
	K5000	P5200				
	K5200	P6000				
	K6000	GP100				
Quadro Mobility	K510M	M500M	P500	N/A	T1000	Windows 7/10 (64-bit) 431.86
	K610M	M520M	P520		T2000	
	K620M	M600M	P600		RTX 3000	Linux (64-bit) 430.50
	K1100M	M620M	P620		RTX 4000	
	K2100M	M1000M	P1000		RTX 5000	
	K2200M	M2000M	P2000			
	K3100M	M2200M	P3000			

Products	GPU Model					Driver Version
	K (Kepler)	M (Maxwell)	P (Pascal)	V (Volta)	RTX	
	K4100M	M3000M	P3200			
	K5100M	M4000M	P4000			
		M5000M	P4200			
			P5000			
			P5200			



Note:

Minimum OpenGL 3.2 and OpenCL 2.1 Requirement

Virtual server/clients and VirtualGL setups may work, but are not officially tested or supported.

NVIDIA Optimus or AMD Switchable Graphics

In order to ensure best performance, these options should be set to use discrete NVIDIA or AMD GPU and not the Intel GPU.

Power Options and Mobility Center

In order to ensure best performance, these options should be maximum performance for both GPU and CPU.

Graphics Driver Corruption or Installation Issues

In order to ensure best driver compatibility, it is recommended to use "Custom" and "Clean" install options instead of the general "Express" driver installer options.

Recommended Workstation Desktop and Laptop/ Notebook Hardware

DELL Workstations - Desktops

Product	Workstation Model				
	3420T / 3430T	3620T / *3630T *3930 Rack	5810	5820 / 7820	7920
NVIDIA Quadro GPU	P400 P600 P620 P1000	P400 P600 P620 P1000 P2000 P4000 P5000 *RTX 4000 *RTX 5000	P400 P600 P1000 P2000 P4000 P6000	P620 P1000 P2000 P4000 P5000 P6000 GP100 RTX 5000 RTX 6000	P620 P1000 P2000 P4000 P5000 P6000 GP100 RTX 5000 RTX 6000
AMD FirePro™ & Raedon™ Pro GPU	WX 2100 WX 3100 WX 4100	WX 2100 WX 3100 WX 4100 WX 5100 WX 7100	W7100 W8100 W9100 WX 4100 WX 5100 WX 7100 WX 9100	WX 2100 WX 3100 WX 4100 WX 5100 WX 7100 WX 9100	WX 2100 WX 3100 WX 4100 WX 5100 WX 7100 WX 9100

DELL Workstations - Laptops

Product	Workstation Model				
	5520 AIO	5520	5530	5720	7520
NVIDIA Quadro GPU	N/A	M1200M	P1000M P2000M	N/A	P3000M P5000M

Product	Workstation Model					
	Precision Workstation	5520 AIO	5520	5530	5720	7520
AMD FirePro™ & Raedon™ Pro GPU	WX 4150	N/A	N/A	WX7100M	WX 7100	

DELL Workstations - Laptops (continued)

Product	Workstation Model					
	Precision Workstation	7720	7530	7730	7540	7740
NVIDIA Quadro GPU	M1200M P3000M P4000M P5000M	P2000M P3200M P4000M	P3200M P4200M P5200M	RTX 3000	RTX 3000	
AMD FirePro™ & Raedon™ Pro GPU	WX 7100	WX 4150	WX 4150 WX 7100	WX 3200	WX 7130	

Lenovo Workstations - Desktops

Product	Workstation Model						
	Lenovo ThinkStation	P320	P320 SFF	P330 TWR / P330 SFF	P330 Tiny	P520	P720
NVIDIA Quadro GPU	P400 P600 P1000 P2000 P4000	P400 P600 P1000	P400 P620 P1000 P2000 P2200 P4000	P620 P1000	P400 P600 P620 P1000 P2000 P2200 P4000 P5000	P400 P600 P620 P1000 P2000 P2200 P4000 P5000 P6000	P400 P600 P620 P1000 P2000 P2200 P4000 P5000 P6000

Product	Workstation Model						
Lenovo ThinkStation	P320	P320 SFF	P330 TWR / P330 SFF	P330 Tiny	P520	P720	P920
						GP100	GP100
AMD FirePro™ & Raedon™ Pro GPU	N/A	N/A	N/A	N/A	N/A	N/A	N/A

Lenovo Workstations - Laptops (*Windows 10 support only)

Product	Workstation Model							
Lenovo ThinkPad	P40 Yoga	P50s	P50	P51s	P51	P1 Gen1	P52s	P52
NVIDIA Quadro GPU	M500M	M500M	M1000M M2000M	M520M	M1200M M2200M	P1000M P2000M	P500	P1000 P2000 P3200
AMD FirePro™ & Raedon™ Pro GPU	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A

Lenovo Workstations - Laptops (*Windows 10 support only) (continued)

Product	Workstation Model						
Lenovo ThinkPad	P43s*	P53s*	P53*	P1 Gen2*	P71	P72	P73*
NVIDIA Quadro GPU	P520	P520	T1000 T2000 RTX 3000 RTX 4000	T1000 T2000	M620M P3000 P4000 P5000	P600 P2000 P3200 P4200 P5200	P620 T2000 RTX 3000 RTX 4000 RTX 5000

Product	Workstation Model						
Lenovo ThinkPad	P43s*	P53s*	P53*	P1 Gen2*	P71	P72	P73*
AMD FirePro™ & Raedon™ Pro GPU	N/A	N/A	N/A	N/A	N/A	N/A	N/A

Acer Workstations and Laptops (*Windows 10 support only)

Product	Workstation Model		
Acer	ConceptD 500*	ConceptD 700*	Veriton K8
NVIDIA Quadro GPU	RTX 4000	RTX 4000	RTX 4000
AMD FirePro™ & Raedon™ Pro GPU	N/A	N/A	N/A

Product	Mobile Workstation Model			
Acer	ConceptD 3 Pro*	ConceptD 5 Pro* (CN515-71P)	ConceptD 5 Pro* (CN517-71P)	ConceptD 7 Pro*
NVIDIA Quadro GPU	T1000	T1000	RTX 3000	RTX 3000 RTX 5000
AMD FirePro™ & Raedon™ Pro GPU	N/A	N/A	N/A	N/A

Altos Workstations and Laptops (*Windows 10 support only)

Product	Workstation Model	
Altos Computing	BrainSphere™ P130 F5	BrainSphere™ P530 F4
NVIDIA Quadro GPU	RTX 2000	K420 P400 K620 K1200 P1000 P2000 P4000 P5000 P6000 GP100 RTX 2000 RTX 4000 RTX 5000
AMD FirePro™ & Raedon™ Pro GPU	N/A	N/A

Comments

For NVIDIA GPU based laptops/notebooks the Optimus power saving option in the BIOS should be disabled and the NVIDIA drivers properly installed for optimal performance in HyperWorks.

For AMD GPU based laptops/notebooks; the Enduro/Switchable Graphics power saving option should be disabled and the AMD drivers properly installed for optimal performance in HyperWorks.

Optimus (Intel/NVIDIA) enabled drivers may create performance issues with notebooks/laptops compared to a dedicated non-shared GPU driver. Disabling the Optimus feature in BIOS, if available, will help give the best overall graphics performance.

Disable nView Window manager under NVIDIA drivers if you experience random crashes and/or issues.

All power saving modes, settings and governors for CPU frequencies and GPU performance should be set to maximum settings in order to get the optimal performance out of HyperWorks. This includes smooth graphics and high frame rates (FPS) on Windows and Linux platforms.

HyperWorks 2020 Solver Hardware Configuration Recommendations

Recommended hardware configurations for HyperWorks Solvers.

AcuSolve Solver

Problem Size	Small	Medium	Large
Typical Workload Steady State or Transient	Steady state: Up to 1M nodes Transient: Up to 100K nodes	Steady state: Up to 10M nodes Transient: Up to 1M nodes	Steady state: Greater than 10M nodes Transient: Greater than 1M nodes
Throughput ¹	Single job	Single job	Single job
CPU ²	Dual CPU socket For example, Intel Xeon Gold "Cascade Lake" or "Skylake" or AMD EPYC 7002 series	Dual CPU socket For example, Intel Xeon Gold "Cascade Lake" or "Skylake" or AMD EPYC 7002 series	Dual CPU socket For example, Intel Xeon Gold "Cascade Lake" or "Skylake" or AMD EPYC 7002 series
Number of CPU / node	1-4	1-4	1-4
Number of cores / node	32 - 128	32 - 128	32 - 128
Number of nodes	1-8	8 - 48	>48
Minimum Memory Configuration / node ³	300MB to 3GB	3GB to 30GB	More than 30GB (3KB per CFD node)
Storage (minimum)	500 GB SATA or SSD	1.5 TB local storage	1.5 TB local storage
Network Interconnect	Gigabit Ethernet Or Infiniband	Infiniband or Intel Omni-path	Infiniband or Intel Omni-path
Operating System	Linux kernel 2.6.32 or higher Windows 7 or 10	Linux kernel 2.6.32 or higher	Linux kernel 2.6.32 or higher
GPU	Yes	Yes	Yes
MPI	Intel MPI 2018.4 or higher	Intel MPI 2018.4 or higher	Intel MPI 2018.4 or higher

Problem Size	Small	Medium	Large
Setup (2000-3000 computational nodes per core)	Pure OpenMP or Hybrid OpenMP/MPI	Hybrid OpenMP/MPI	Hybrid OpenMP/MPI
Hyper Threading	Not recommended	Not recommended	Not recommended

Feko Solver

Problem Size	Small	Medium	Large
General recommendations given for MoM and MLFMM dependent on problem size in terms of number of unknowns / mesh elements. For other solution methods (FEM, FDTD, RL-GO, PO, UTD) many factors to be considered.	Pure MoM: less than 50k unknowns. MLFMM: between 100k and 500k unknowns	Pure MoM: between 50k and 100k unknowns. MLFMM: between 500k and 5M unknowns	Pure MoM: >100k unknowns MLFMM: >5M unknowns
Throughput ¹	Single job	Single large job or few jobs in parallel	Single very large job or multiple jobs
CPU ²	Dual CPU socket For example, Intel Xeon Gold "Cascade Lake" or "Skylake" or later	Dual CPU socket For example, Intel Xeon Gold "Cascade Lake" or "Skylake" or later	Dual CPU socket For example, Intel Xeon Gold "Cascade Lake" or "Skylake" or later
Number of CPU / node	2	2	2
Number of cores / node	32 – 56	32 – 56	32 – 56
Number of nodes	1	8 – 16	> 16
Minimum Memory Configuration / node ³	64 GB	128 GB	256 GB
Storage (minimum)	500 GB SATA or SSD	500 GB SATA or SSD	500 GB SATA or SSD
Network Interconnect	Gigabit Ethernet	Infiniband or Intel Omni-path	Infiniband or Intel Omni-path

Problem Size	Small	Medium	Large
Operating System	Linux kernel 2.6.32 or higher Windows 7 or 10	Linux kernel 2.6.32 or higher	Linux kernel 2.6.32 or higher
GPU	Yes	No	No
MPI	Intel MPI 2018.4 or higher	Intel MPI 2018.4 or higher	Intel MPI 2018.4 or higher
Setup	Pure MPI	Pure MPI	Pure MPI
Hyper Threading	Not recommended	Not recommended	Not recommended

Flux Solver

Problem type	Small	Medium	Large
Typical Workload (depending on number of DOF, element type, and other factors)	< 300 000 DOF	Around 500 000 DOF	Around 5M DOF
Throughput ¹	Single	Single	Single
CPU ²	Dual CPU socket For example, Intel Xeon Gold "Cascade Lake" or "Skylake"	Dual CPU socket For example, Intel Xeon Gold "Cascade Lake" or "Skylake"	Dual CPU socket For example, Intel Xeon Gold "Cascade Lake" or "Skylake"
Number of CPU / node	1	2	2
Number of cores / node	8	16	16+
Number of nodes	1	1	1-4
Minimum Memory Configuration / node ³	8 GB	16-32 GB	300GB
Storage (minimum)	500 GB SATA or SSD	1 TB local storage SSD	1.5 TB local storage SSD
Network Interconnect			Infiniband or Intel Omni-path
Operating System	Linux kernel 3.10.0-693 or higher	Linux kernel 3.10.0-693 or higher	Linux kernel 3.10.0-693 or higher

Problem type	Small	Medium	Large
	Windows 7 or 10 with SSD	Windows 7 or 10 with SSD	Windows 7 or 10 with SSD
GPU	No	No	No
MPI	Intel MPI 2018.4 or higher	Intel MPI 2018.4 or higher	Intel MPI 2018.4 or higher
Setup	SMP	SMP or Hybrid 2MPI/node	SMP or Hybrid 2MPI/node
Hyper Threading	Not recommended	Not recommended	Not recommended

Radioss Solver

Problem Size	Small	Medium	Large
Typical Workload Crash & Impact	Component tests, sled test, drop test, ... Less than 500K elements	Medium crash model, between 1 and 6 millions of elements model	Accurate car crash model (rupture), very large model with size > 6 million elements
Throughput ¹	Single job	Single large job or few jobs in parallel	Single very large job or multiple jobs
CPU ²	Dual CPU socket For example, Intel Xeon Gold "Cascade Lake" or "Skylake" or AMD EPYC 7002 series	Dual CPU socket For example, Intel Xeon Gold "Cascade Lake" or "Skylake" or AMD EPYC 7002 series	Dual CPU socket For example, Intel Xeon Gold "Cascade Lake" or "Skylake" or AMD EPYC 7002 series
Number of CPU / node	2	2	2
Number of cores / node	32 – 64	32 – 128	32 – 128
Number of nodes	1	8 – 16	> 16
Minimum Memory Configuration / node ³	64-128GB	64-128GB	64-128GB
Storage (minimum)	500 GB SATA or SSD	1,5 TB local storage	1,5 TB local storage
Network Interconnect	Gigabit Ethernet	Infiniband or Intel Omni-path	Infiniband or Intel Omni-path

Problem Size	Small	Medium	Large
Operating System	Linux kernel 2.6.32 or higher Windows 7 or 10	Linux kernel 2.6.32 or higher	Linux kernel 2.6.32 or higher
GPU	No	No	No
MPI	Intel MPI 2018.4 or higher	Intel MPI 2018.4 or higher	Intel MPI 2018.4 or higher
Setup	Pure MPI	Pure MPI or Hybrid with 2 or 4 OpenMP threads per MPI	Hybrid with 2 or 4 OpenMP threads per MPI
Hyper Threading ⁵	Yes, Hybrid with 2 OpenMP per MPI	Not recommended	Not recommended

OptiStruct Solver

Problem type	Small or medium	Large static	Large dynamic
Typical Workload (depending on number of DOF, element type, and other factors)	Nonlinear - less than 2M DOF; linear static - less than 5M DOF; NVH - less than 5M DOF	Nonlinear - more than 2M DOF; linear static - more than 5M DOF	NVH - more than 5M DOF
Throughput ¹	Single	Single	Single or few jobs in parallel
CPU ²	Dual CPU socket For example, Intel Xeon Gold "Cascade Lake" or "Skylake"	Dual CPU socket For example, Intel Xeon Gold "Cascade Lake" or "Skylake"	Dual CPU socket For example, Intel Xeon Gold "Cascade Lake" or "Skylake"
Number of CPU / node	2	2	2
Number of cores / node	8-24	24+	24+
Number of nodes	1	1-8	1-8
Minimum Memory Configuration / node ³	16-64GB	128GB	256GB

Problem type	Small or medium	Large static	Large dynamic
Storage (minimum)	512GB local storage	1TB local storage	3 TB local storage, SSD and RAID0 recommended
Network Interconnect		InfiniBand or Intel Omni-path	InfiniBand or Intel Omni-path
Operating System	Linux kernel 2.6.32 or higher Windows 7 or 10 with SSD	Linux kernel 2.6.32 or higher Windows 7 or 10 with SSD	Linux kernel 2.6.32 or higher Windows 7 or 10 with SSD
GPU	Yes	No	No
MPI	Intel MPI 2018.4 or higher	Intel MPI 2018.4 or higher	Intel MPI 2018.4 or higher
Setup	SMP or DDM hybrid	DDM hybrid	SMP or DDM hybrid
Hyper Threading	Not recommended	Not recommended	Not recommended

1. Number of simultaneous jobs. Use of a workload management middleware like Altair PBS is highly recommended to insure optimal and dedicated usage of the CPU resource
2. Typical node configuration is based on dual CPU socket processors
3. It is extremely important to populate all the memory banks on the mother board.
4. In Hybrid mode, it is recommended to set a number of MPIs that is a multiple of the number of sockets and then set the number of OpenMP in a way that number of MPIs x number of OpenMP equal number of physical cores.
5. Hyper Threading (HT) may increase performance by around 10% on single node. In this case, recommended setup is to run 2 OpenMP per MPI, with a number of MPIs that matches the total number of physical cores on the node. On multi-node, it is better not using HT

Recommended GPU Computing Processor List for OptiStruct

Recommended graphic boards for use with the Altair HyperWorks solver suite of applications for high-powered GPU computing.

The following table lists the recommended graphic boards for use with the Altair HyperWorks solver suite of applications for high-powered GPU computing.

Manufacturer and Model	Graphics Card	Driver Version (Minimum or Higher)
NVIDIA (Tesla)	P100 V100	Linux (64-bit) 387.26 Windows (64-bit) 391.03
NVIDIA (Quadro)	GP100 GV100	Linux (64-bit) 387.26 Windows (64-bit) 391.03



Note: The most recent vendor/manufacturer drivers should be used and all driver support for these cards should be addressed to the appropriate manufacturer of the graphics board.

Additional Information on Driver Installations

The NVIDIA Driver Update recommendation is to use the **Custom installation** option and select the **Perform clean installation** option to validate that there are no conflicts in DLL/drivers.

The same should be done with AMD hardware and drivers as well using AMD's custom uninstall tools.



Figure 1: